

REVISIONS			
SYM.	DESCRIPTION	DATE	APPROVED
A	RELEASED	06/10/99	T.L.
B	REVISED PER DCN 17245	12/12/00	T.L.
C	REDRAWN PER DCN 22773	08/20/04	E.L.

DASH NO	NOMINAL I.D.	NO OF CARRIERS PER LAYER	NO OF ENDS PER LAYER	CURRENT RATING AMPS	LBSY 100 FT
031	.031	24	24	7.0	.20
062	.062	24	48	11.0	.40
078	.078	24	72	16.0	.60
109	.109	24	96	19.0	.83
125	.125	24	120	25.0	1.03
156	.156	24	240	40.0	2.09
171	.171	24	168	32.0	1.43
188	.188	24	192	33.0	1.63
203	.203	24	312	46.0	2.80
250	.250	24	384	53.0	3.45
375	.375	48	384	53.0	3.95
500	.500	48	528	62.0	4.77
625	.625	48	720	85.0	5.94
781	.781	48	864	88.0	7.35
937	.937	64	640	65.0	5.83
1000	1.000	64	768	90.0	7.50
1250	1.250	72	792	T80	T80
1375	1.375	72	864	T80	T80
1500	1.500	72	936	T80	T80
2000	2.000	96	1152	T80	T80
2500	2.500	96	1248	T80	T80

TABLE I - 36 AWG



UNLESS OTHERWISE SPECIFIED DIMENSIONS ARE IN INCHES

TOLERANCES:

FRACTIONS ± 1/16

DECIMALS .XX ± .03

ANGLES ± 2°

DO NOT SCALE THIS DRAWING

B/F 99-7281 P/C 100

NON REPAIRABLE COMMERCIAL ITEM

RELEASE DATE 06/10/99

DRAWN T.L.E 06/09/99

CHECK P.D. 06/09/99

ENGR R. PAINTER 06/09/99

CODE IDENT. NO. SIZE 06324

SCALE N/A

WEIGHT N/A

SHEET 1 OF 1

REV. C 100-002

GLENAIR, INC.

1211 AIR WAY - GLENDALE - CALIFORNIA 91201

CAO 1995°

BRAID, SINGLE LAYER TUBULAR, SILVER/COPPER

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES

BASIC NO

A = 36 AWG

B = 34 AWG

DASH NO TABLE I

INSERT LETTER L FOR LANYARD (OMIT FOR NONE)

PART NUMBER DEVELOPMENT

EXAMPLE:

100 - 002 A 203 L

PRODUCT SERIES