

**15A, 1200V Ultrafast Dual Diode**

The RURG15120CC is an ultrafast dual diode with soft recovery characteristics ( $t_{rr} < 100\text{ns}$ ). It has low forward voltage drop and is of silicon nitride passivated ion-implanted epitaxial planar construction.

This device is intended for use as a freewheeling/clamping diode and rectifier in a variety of switching power supplies and other power switching applications. Its low stored charge and ultrafast soft recovery minimize ringing and electrical noise in many power switching circuits, thus reducing power loss in the switching transistors.


Formerly developmental type TA49097.

**Ordering Information**

| PART NUMBER | PACKAGE | BRAND     |
|-------------|---------|-----------|
| RURG15120CC | TO-247  | URG15120C |

NOTE: When ordering, use the entire part number.

**Symbol**



**Features**


- Ultrafast with Soft Recovery . . . . . <100ns
- Operating Temperature. . . . . 175°C
- Reverse Voltage . . . . . 1200V
- Avalanche Energy Rated
- Planar Construction

**Applications**

- Switching Power Supplies
- Power Switching Circuits
- General Purpose

**Packaging**

JEDEC STYLE TO-247



**Absolute Maximum Ratings** (Per Leg)  $T_C = 25^\circ\text{C}$ , Unless Otherwise Specified

|  | RURG15120CC | UNITS |
|--|-------------|-------|
| Peak Repetitive Reverse Voltage . . . . . $V_{RRM}$                                      | 1200        | V     |
| Working Peak Reverse Voltage . . . . . $V_{RWM}$   | 1200        | V     |
| DC Blocking Voltage . . . . . $V_R$  | 1200        | V     |
| Average Rectified Forward Current . . . . . $I_{F(AV)}$<br>( $T_C = 140^\circ\text{C}$ ) | 15          | A     |
| Repetitive Peak Surge Current . . . . . $I_{FRM}$<br>(Square Wave, 20kHz)                | 30          | A     |
| Nonrepetitive Peak Surge Current . . . . . $I_{FSM}$<br>(Halfwave, 1 Phase, 60Hz)        | 200         | A     |
| Maximum Power Dissipation . . . . . $P_D$  | 100         | W     |
| Avalanche Energy (See Figures 10 and 11) . . . . . $E_{AVL}$                             | 20          | mJ    |
| Operating and Storage Temperature . . . . . $T_{STG}, T_J$                               | -65 to 175  | °C    |

## RURG15120CC

### Electrical Specifications (Per Leg) $T_C = 25^\circ\text{C}$ , Unless Otherwise Specified

| SYMBOL          | TEST CONDITION  | MIN | TYP | MAX | UNITS                     |
|-----------------|---|-----|-----|-----|---------------------------|
| $V_F$           | $I_F = 15\text{A}$                                    | -   | -   | 2.1 | V                         |
|                 | $I_F = 15\text{A}, T_C = 150^\circ\text{C}$           | -   | -   | 1.9 | V                         |
| $I_R$           | $V_R = 1200\text{V}$                                  | -   | -   | 100 | $\mu\text{A}$             |
|                 | $V_R = 1200\text{V}, T_C = 150^\circ\text{C}$         | -   | -   | 500 | $\mu\text{A}$             |
| $t_{rr}$        | $I_F = 1\text{A}, dI_F/dt = 100\text{A}/\mu\text{s}$  | -   | -   | 100 | ns                        |
|                 | $I_F = 15\text{A}, dI_F/dt = 100\text{A}/\mu\text{s}$ | -   | -   | 130 | ns                        |
| $t_a$           | $I_F = 15\text{A}, dI_F/dt = 100\text{A}/\mu\text{s}$ | -   | 65  | -   | ns                        |
| $t_b$           | $I_F = 15\text{A}, dI_F/dt = 100\text{A}/\mu\text{s}$ | -   | 40  | -   | ns                        |
| $Q_{RR}$        | $I_F = 15\text{A}, dI_F/dt = 100\text{A}/\mu\text{s}$ | -   | 400 | -   | nC                        |
| $C_J$           | $V_R = 10\text{V}, I_F = 0\text{A}$                   | -   | 56  | -   | pF                        |
| $R_{\theta JC}$ |   | -   | -   | 1.5 | $^\circ\text{C}/\text{W}$ |

#### DEFINITIONS

$V_F$  = Instantaneous forward voltage (pw = 300 $\mu\text{s}$ , D = 2%).

$I_R$  = Instantaneous reverse current.

$t_{rr}$  = Reverse recovery time (See Figure 9), summation of  $t_a + t_b$ .

$t_a$  = Time to reach peak reverse current (See Figure 9).

$t_b$  = Time from peak  $I_{RM}$  to projected zero crossing of  $I_{RM}$  based on a straight line from peak  $I_{RM}$  through 25% of  $I_{RM}$  (See Figure 9).

$Q_{RR}$  = Reverse recovery charge.

$C_J$  = Junction capacitance.

$R_{\theta JC}$  = Thermal resistance junction to case.

pw = pulse width.

D = duty cycle.

### Typical Performance Curves




FIGURE 1. FORWARD CURRENT vs FORWARD VOLTAGE




FIGURE 2. REVERSE CURRENT vs REVERSE VOLTAGE

Typical Performance Curves (Continued)




FIGURE 3.  $t_{rr}$ ,  $t_a$  AND  $t_b$  CURVES vs FORWARD CURRENT




FIGURE 4.  $t_{rr}$ ,  $t_a$  AND  $t_b$  CURVES vs FORWARD CURRENT




FIGURE 5.  $t_{rr}$ ,  $t_a$  AND  $t_b$  CURVES vs FORWARD CURRENT




FIGURE 6. CURRENT DERATING CURVE




FIGURE 7. JUNCTION CAPACITANCE vs REVERSE VOLTAGE

Test Circuits and Waveforms




FIGURE 8.  $t_{rr}$  TEST CIRCUIT




FIGURE 9.  $t_{rr}$  WAVEFORMS AND DEFINITIONS

$I = 1A$   
 $L = 40mH$   
 $R < 0.1\Omega$   
 $E_{AVL} = 1/2LI^2 [V_{R(AVL)}/(V_{R(AVL)} - V_{DD})]$   
 $Q_1 = IGBT (BV_{CES} > DUT V_{R(AVL)})$




FIGURE 10. AVALANCHE ENERGY TEST CIRCUIT




FIGURE 11. AVALANCHE CURRENT AND VOLTAGE WAVEFORMS

All Intersil semiconductor products are manufactured, assembled and tested under **ISO9000** quality systems certification.

*Intersil semiconductor products are sold by description only. Intersil Corporation reserves the right to make changes in circuit design and/or specifications at any time without notice. Accordingly, the reader is cautioned to verify that data sheets are current before placing orders. Information furnished by Intersil is believed to be accurate and reliable. However, no responsibility is assumed by Intersil or its subsidiaries for its use; nor for any infringements of patents or other rights of third parties which may result from its use. No license is granted by implication or otherwise under any patent or patent rights of Intersil or its subsidiaries.*

For information regarding Intersil Corporation and its products, see web site [www.intersil.com](http://www.intersil.com)