

S21MD3V

High Noise Resistance Type Phototriac Coupler

* Lead forming type and taping reel type are also available. (S21MD3W/S21MD3P)

** TÜV (VDE0884) approved type is also available as an option.

■ Features

1. High critical rate of rise of OFF-state voltage
(dv/dt : MIN. 500V/ μ s)
2. High repetitive peak OFF-state voltage
(V_{DRM} : MIN. 600V)
3. Isolation voltage between input and output
V_{iso} : 5 000Vrms
4. UL recognized, file No.E64380 (S21MD3V / S21MD3W)


* S21MD3V is for 200V line.

■ Applications

1. For triggering medium/high power triac

■ Outline Dimensions

(Unit : mm)



■ Absolute Maximum Ratings

(Ta = 25°C)

	Parameter	Symbol	Rating	Unit
Input	Forward current	I _F	50	mA
	Reverse voltage	V _R	6	V
Output	RMS ON-state current	I _T	100	mA _{rms}
	* ¹ Peak one cycle surge current	I _{surge}	1.2	A
	Repetitive peak OFF-state voltage	V _{DRM}	600	V
	* ² Isolation voltage	V _{iso}	5 000	V _{rms}
	Operating temperature	T _{opr}	- 30 to + 100	°C
	Storage temperature	T _{stg}	- 55 to + 125	°C
	* ³ Soldering temperature	T _{sol}	260	°C

*1 Sine wave

*2 40 to 60% , RH

AC 1 minute, f = 60Hz

*3 For 10 seconds

■ Electro-optical Characteristics

(Ta = 25°C)

Parameter		Symbol	Conditions	MIN.	TYP.	MAX.	Unit
Input	Forward voltage	V _F	I _F = 30mA	-	1.2	1.4	V
	Reverse current	I _R	V _R = 3V	-	-	10 ⁻⁵	A
Output	Repetitive peak OFF-state current	I _{DRM}	V _{DRM} = Rated	-	-	10 ⁻⁶	A
	On-state voltage	V _T	I _T = 100mA	-	1.7	2.5	V
	Holding current	I _H	V _D = 6V	0.1	1	3.5	mA
Transfer characteristics	Critical rate of rise of OFF-state voltage	dV/dt	V _{DRM} = 1/4 $\sqrt{2}$ Rated	500	-	-	V/ μ s
	Minimum trigger current	I _{FT}	V _D = 6V, R _L = 100Ω	-	-	15	mA
	Isolation resistance	R _{ISO}	DC500V, 40 to 60% RH	5 x 10 ¹⁰	10 ¹¹	-	Ω
Turn-on time	t _{on}		V _D = 6V, I _F = 30mA, R _L = 100Ω	-	100	250	μs

Fig. 1 RMS ON-state Current vs.
Ambient Temperature




Fig. 2 Forward Current vs.
Ambient Temperature




Fig. 3 Forward Current vs. Forward Voltage




Fig. 4 Minimum Trigger Current vs.
Ambient Temperature




Fig. 5 Relative Repetitive Peak OFF-state Voltage vs. Ambient Temperature




Fig. 6 ON-state Voltage vs. Ambient Temperature




Fig. 7 Holding Current vs. Ambient Temperature




Fig. 8 Repetitive Peak OFF-state Current vs OFF-state Voltage




Fig. 9 Repetitive Peak OFF-state Current vs. Ambient Temperature






Fig. 10 Turn-on Time vs. Forward Current




**Fig.11 ON-state Current vs.
ON-state Voltage**



■ Basic Operation Circuit

Medium/High Power Triac Drive Circuit



Note) Please use on condition of the triac for power triggers.

- Please refer to the chapter “Precautions for Use” (Page 78 to 93).