


3-phase full-wave fan motor driver IC

BA6425FS

● Description

BA6425FS is a 3-phase full-wave fan motor driver IC. Noise generated by the motor can be reduced by linear driving system. Forward/reverse rotation can be switched. This IC has current limit circuit and FG output.

● Dimension (Units : mm)



SSOP-A32

● Features

- 1) Linear driving system
- 2) Forward/reverse select switch
- 3) Built-in current limiter and thermal shut down
- 4) FG output

● Applications

3-phase full-wave fan motor

● Absolute Maximum Ratings ($T_a=25^{\circ}\text{C}$)

Parameter	Symbol	Limits	Unit
Maximum supply voltage	Vcc	18	V
Maximum supply voltage	VM	18	V
Power dissipation	Pd	0.95 ^{*1}	W
Operating temperature range	Topr	-30 ~ +75	°C
Storage temperature range	Tstg	-55 ~ +150	°C
Output current	Iomax	1000 ^{*2}	mA
Junction temperature	Tjmax	150	°C

*1 Derating : 7.6mW/°C for operation above $T_a=25^{\circ}\text{C}$. PCB (70mmx70mm, t=1.6mm) glass epoxy mounting.

*2 However, do not exceed Pd, and ASO.

● Recommended Operating Conditions ($T_a=25^\circ C$)

Parameter	Symbol	Min.	Typ.	Max.	Unit
Operating supply voltage range	Vcc	5	—	17	V
Operating supply voltage range	VM	3.5	—	17 *3	V
Hall Amp in-phase voltage range	VCH	1.1	—	Vcc-1.0	V

*If VM voltage is low, this IC may not be able to flow the output current by absolute maximum ratings.

● Electrical characteristics (Unless otherwise noted: $T_a=25^\circ C$, $Vcc=VM=12V$)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Vcc circuit current	Icc	—	3.7	6.0	mA	Output : Open, Input : HLH
VM circuit current	IM	—	76	120	μA	Output : Open, Input : HLH
Output saturation voltage H	VOH	0.8	1.21	1.6	V	$Io=350mA$
Output saturation voltage L	VOL	0.35	0.55	0.75	V	$Io=350mA \ RNF=0.5\Omega$
Hall bias current H1	IBH1	-4.0	—	2.0	μA	
Hall bias current H2, H3	IBH2	—	—	2.0	μA	
Input-converted offset voltage	ISD	-10	—	10	mV	
Current limit voltage	VCL	0.38	0.5	0.62	V	$RNF=0.5\Omega$
FR bias current	IFRL	-2.0	—	0	μA	
Forward input voltage range	VFRH	7.5	—	Vcc	V	
Reverse input voltage range	VFRL	0	—	4.5	V	
FG output L voltage	VFGL	—	—	0.2	V	$Io=2mA$
FG hysteresis width	VHYS	± 8	± 18	± 28	mV	

● Application Circuit

