



Description:

This package contains six inverters.

Mode of operation:

All six inverters can be used independently of one another. For each inverter, a low input gives a high output and vice versa. The 7414 contains six inverters with Schmitt-trigger inputs and has the same pinout.

Application:

Logical inversion, pulse shaping, oscillators

Data:

Propagation delay	ns	10	6	2.75	3.5	6	33	9.5	3
Supply current	mA	12	2	8	6.9	26	1.2	3	23
Families:		Std	ALS	AS	F	H	L	LS	S
		●	●	●	●	●	●	●	●

Hex INVERTER

7404