

# LM331


## V-F Converter

### Features


- Guaranteed linearity: 0.01% max.
- Low power dissipation: 15mW at 5V
- Wide range of full scale frequency: 1Hz to 100KHz
- Pulse output compatible with all logic forms
- Wide dynamic range: 100dB min at 10KHz full scale frequency

### Description

This voltage to frequency converter provides the output pulse train at a frequency precisely proportional to the applied input voltage. The LM331 can operate at power supplies as low as 4.0V and be changed output frequency from 1Hz to 100KHz. It is ideally suited for use in simple low cost circuit for analog-to digital conversion, long term integration, linear frequency modulation or demodulation, frequency to voltage conversion, and many other functions.



### Internal Block Diagram



**Absolute Maximum Ratings (TA = 25°C)**

Parameter	Symbol	Value	Unit
Supply Voltage	VCC	40	V
Input Voltage	VI	-0.2 ~ + VCC	V
Operating Temperature Range	TOPR	0 ~ +70	°C
Power Dissipation	PD	500	mW

**Electrical Characteristics**

Parameter	Symbol	Conditions	Min.	Typ.	Max.	Unit
VFC Non-Linearity	VFCNL	$4.5 \leq V_{CC} \leq 20V$	-	$\pm 0.003$	$\pm 0.01$	% Full-Scale
Conversion Accuracy Scale Factor	ACCUR	$V_I = -10V, R_S = 14K\Omega$	0.90	1.00	1.10	KHz/V
Change Of Gain With VCC	VCC $\Delta$ G/VCC	$4.5V \leq V_{CC} \leq 10V$	-	0.01	0.1	% / V
		$10V \leq V_{CC} \leq 40V$	-	0.006	0.06	
Rated Full - Scale Frequency	f	$V_I = -10V$	10.0	-	-	KHz
<b>INPUT COMPARATOR</b>						
Offset Voltage	V <sub>IO</sub>	$0^\circ C \leq T_A \leq +70^\circ C$	-	$\pm 3$	$\pm 10$	mV
Bias Current	I <sub>BIAS</sub>	-	-	-80	-300	nA
Offset Current	I <sub>IO</sub>	-	-	$\pm 8$	$\pm 100$	nA
Common-Mode Range	V <sub>CM</sub>	$0^\circ C \leq T_A \leq +70^\circ C$	-0.2	-	VCC-2.0	V
<b>TIMER (PIN 5)</b>						
Timer Threshold Voltage	V <sub>TH</sub>	-	0.63	0.667	0.701	$\times V_{CC}$
Input Bias Current	I <sub>BIAS</sub>	$V_{CC} = 15V, 0V \leq V_5 \leq 9.9V$	-	$\pm 10$	$\pm 100$	nA
		$V_5 = 10V$	-	200	1000	nA
Saturation Voltage	V <sub>SAT</sub>	$I = 5mA$	-	0.22	0.5	V
<b>CURRENT SOURCE (PIN 1)</b>						
Output Current	I <sub>O</sub>	$R_S = 14K\Omega, V_1 = 0V$	116	136	156	$\mu A$
Change with Voltage	$\Delta I_O / \Delta V_1$	$0V \leq V_1 \leq 10V$	-	0.2	1.0	$\mu A$
Current Source Off Leakage	I <sub>LKG</sub>	-	-	0.02	10.0	nA
<b>REFERENCE VOLTAGE (PIN 2)</b>						
Reference Voltage	V <sub>REF</sub>	-	1.70	1.89	2.08	V <sub>DC</sub>
Stability vs Temperature	ST <sub>T</sub>	-	-	$\pm 60$	-	ppm/°C
Stability vs Time, 1000Hours	ST <sub>T</sub>	-	-	$\pm 0.1$	-	%
<b>LOGIC OUTPUT (Pin 3)</b>						
Saturation Voltage	V <sub>SAT</sub>	$I = 5mA$	-	0.15	0.50	V
		$I = 3.2mA$	-	0.10	0.40	
Off Leakage	I <sub>LKG</sub>	-	-	$\pm 0.05$	1.0	$\mu A$
<b>SUPPLY CURRENT</b>						
Supply Current	I <sub>CC</sub>	$V_{CC} = 5V$	1.5	3.0	6.0	mA
		$V_{CC} = 40V$	2.0	4.0	8.0	

## Typical Applications




Figure 1. Precision Voltage-to-Frequency Converter, 100KHz Full-Scale




Figure 2. Simple Frequency-to-Voltage Converter, 10KHz Full-Scale





Figure 3. Light Intensity to Frequency Converter

# Mechanical Dimensions

## Package

Dimensions in millimeters

### 8-DIP



---

**Ordering Information**

Product Number	Package	Operating Temperature
LM331N	8-DIP	0 ~ +70°C

**EEPW** 电子產品世界  
.com.cn



**DISCLAIMER**

FAIRCHILD SEMICONDUCTOR RESERVES THE RIGHT TO MAKE CHANGES WITHOUT FURTHER NOTICE TO ANY PRODUCTS HEREIN TO IMPROVE RELIABILITY, FUNCTION OR DESIGN. FAIRCHILD DOES NOT ASSUME ANY LIABILITY ARISING OUT OF THE APPLICATION OR USE OF ANY PRODUCT OR CIRCUIT DESCRIBED HEREIN; NEITHER DOES IT CONVEY ANY LICENSE UNDER ITS PATENT RIGHTS, NOR THE RIGHTS OF OTHERS.

**LIFE SUPPORT POLICY**

FAIRCHILD'S PRODUCTS ARE NOT AUTHORIZED FOR USE AS CRITICAL COMPONENTS IN LIFE SUPPORT DEVICES OR SYSTEMS WITHOUT THE EXPRESS WRITTEN APPROVAL OF THE PRESIDENT OF FAIRCHILD SEMICONDUCTOR CORPORATION. As used herein:

1. Life support devices or systems are devices or systems which, (a) are intended for surgical implant into the body, or (b) support or sustain life, and (c) whose failure to perform when properly used in accordance with instructions for use provided in the labeling, can be reasonably expected to result in a significant injury of the user.
2. A critical component in any component of a life support device or system whose failure to perform can be reasonably expected to cause the failure of the life support device or system, or to affect its safety or effectiveness.