# Portable High-Performance Multifunction DAQ for USB

# NI DAQPad-6015, NI DAQPad-6016

- 16 analog inputs at up to 200 kS/s, 16-bit resolution
- Multiple signal connectivity options
- 2 analog outputs for accurate output signals
- Up to 32 digital I/O lines (5 V TTL/CMOS)
- OEM version available

## **Operating Systems**

· Windows 2000/XP

### **Recommended Software**

- LabVIEW
- LabWindows/CVI
- Measurement Studio
- VI Logger

# **Other Compatible Software**

- C++
- C#
- Visual Basic

# Measurement Services Software (included)

- NI-DAQmx driver software
- Measurement & Automation Explorer configuration software



Product	Bus	Analog Inputs <sup>1</sup>	Input Resolution	Sampling Rate	Input Range	Analog Outputs	Output Resolution	Output Rate <sup>2</sup>	Output Range	Digital I/O	Counter/Timers	Triggers
NI DAQPad-6015	USB	16 SE/8 DI	16 bits	200 kS/s	±0.05 to ±10 V	2	16 bits	300 S/s	±10 V	8	2	Digital
NI DAQPad-6016	USB	16 SE/8 DI	16 bits	200 kS/s	$\pm 0.05$ to $\pm 10$ V	2	16 bits	300 S/s	±10 V	32	2	Digital
1SF - single ended DI	_ difforo	ntial 2Quetam_danan	dent									

#### Hardware Overview

The National Instruments DAQPad-6015 and DAQPad-6016 multifunction data acquisition (DAQ) devices provide plug-and-play connectivity via USB for acquiring, generating, and logging data in a variety of portable and desktop applications. DAQPad devices with screw terminals or BNC connectors provide direct connectivity so you can easily connect sensors and signals without extra cost. With DAQPad-6015 mass termination, you can cable to external accessories and signal conditioning devices such as NI SCC devices. All devices feature 16-bit accuracy at up to 200 kS/s. The DAQPad-6016 also provides 32 digital I/O lines for applications requiring an extended interface to digital sensors and actuators.

# **Software Overview**

NI DAQPad-6015 and DAQPad-6016 include NI-DAQmx measurement services software with which you can quickly configure and begin taking measurements with your DAQ device. NI-DAQmx provides a seamless interface to LabVIEW, LabWindows/CVI, and Measurement Studio development environments with features such as DAQ Assistant and a single programming interface for all device functions.

### **Recommended Accessories**

	Cal	le	Signal Connectivity			
	Noise-Reducing,	Low-Cost,	Sensors/			
Model	Shielded	Ribbon	Signals >10 V	Signals <10 V		
NI DAQPad-6016						
Screw Terminal						
NI DAQPad-6015	Built-ii	n signal connectivit	y – no accessories ne	eeded		
Screw Terminal						
NI DAQPad-6015 BNC						
NI DAQPad-6015	SH68-68-FP	R6868	SCC signal	SCB-68		
Mass Termination	300-08-EF	NU808	conditioning	3UB-08		
NI DAQPad-6016 OEM	SH50-50	-	Custom or third-party 50-pin conne			
	SH6850	R6850	_	CB-68LP		

Table 2. NI DAQPad-601x Accessory Selection Guide

## **Common Applications**

The DAQPad-6015 and DAQPad-6016 are ideal for a number of applications where portability and accurate measurements are essential, such as:

- Portable data logging log environmental or voltage data quickly and easily
- Field-monitoring applications
- Embedded OEM applications
- In-vehicle data acquisition
- Academic lab use academic discounts are available for quantities of five or more. Visit ni.com/academic for details.



# **Portable High-Performance Multifunction DAQ for USB**

## **Information for OEM Customers**

National Instruments has created a special OEM hardware kit for the DAQPad-6016. It does not include the enclosure, power supply, screw terminals, or printed documentation. Power supplies are sold separately. The OEM hardware kit includes two standard 50-pin connectors for connecting to custom or third-party accessories. For information on quantity pricing for this kit, please contact your local sales representative.

# **Ordering Information**


•	
NI DAQPad-6015	
Screw terminal	779047-0P1
Mass termination	779201-0P1
BNC	779193-0P1
NI DAQPad-6016	
Screw terminal	779025-0P1
Includes NI-DAQmx software.	
<sup>1</sup> P = power, 1 for U.S. (120 V), 2 for Switzerland (220 V), 3 for Austr	ralia (240 V),
4 for Europe (240 V), 6 for UK (240 V), 7 for Japan (100 V)	
NI DAQPad-6016, OEM hardware-only kit	190177-01

# **BUY NOW!**

For complete product specifications, pricing, and accessory information, call (800) 813 3693 (U.S. only) or go to ni.com/daq.

# **NI Services and Support**

NI has the services and support to meet your needs around the globe and through the application life cycle – from planning and development through deployment and ongoing maintenance. We offer services and service levels to meet customer requirements in research, design, validation, and manufacturing.



# **Training and Certification**

NI training is the fastest, most certain route to productivity with our products. NI training can shorten your learning curve, save development time, and reduce maintenance costs over the application life cycle. We schedule instructor-led courses in cities worldwide, or we can hold a course at your facility. We also offer a professional certification program that identifies individuals who have high levels of skill and knowledge on using NI products. Visit ni.com/training.

#### **Professional Services**

Our Professional Services Team is comprised of NI applications engineers, NI Consulting Services, and a worldwide National Instruments Alliance Partner program of more than 600 independent consultants



and integrators. Services range from start-up assistance to turnkey system integration. Visit ni.com/alliance.

# **OEM Support**

We offer design-in consulting and product integration assistance if you want to use our products for OEM applications. For information about special pricing and services for OEM customers, visit ni.com/oem.

# **Local Sales and Technical Support**

In offices worldwide, our staff is local to the country, giving you access to engineers who speak your language. NI delivers industry-leading technical support through online knowledge bases, our applications engineers, and access to 14,000 measurement and automation professionals within NI Developer Exchange forums. Find immediate answers to your questions at ni.com/support.

We also offer service programs that provide automatic upgrades to your application development environment and higher levels of technical support. Visit ni.com/ssp.

# Hardware Services NI Factory Installation Services

NI Factory Installation Services (FIS) is the fastest and easiest way to use your PXI or PXI/SCXI combination systems right out of the box. Trained NI technicians install the software and hardware and configure the system to your specifications. NI extends the standard warranty by one year on hardware components (controllers, chassis, modules) purchased with FIS. To use FIS, simply configure your system online with ni.com/pxiadvisor.

#### **Calibration Services**

NI recognizes the need to maintain properly calibrated devices for high-accuracy measurements. We provide manual calibration procedures, services to recalibrate your products, and automated calibration software specifically designed for use by metrology laboratories. Visit ni.com/calibration.

#### **Repair and Extended Warranty**

NI provides complete repair services for our products. Express repair and advance replacement services are also available. We offer extended warranties to help you meet project life-cycle requirements. Visit ni.com/services.



ni.com • (800) 813 3693

National Instruments • info@ni.com